VT3-OL SERIES **Three-Phase Voltage Transducers**

The VT3-OL Series Voltage Transducers are high-performance, True RMS transducers designed for accurate voltage sensing in three-phase applications. Housed in a DIN rail or panel mount case, the VT3 monitors common three-phase voltage ranges (120, 240, and 480 VAC) up to 600 VAC and includes Phase Loss Detection with an SPST Form A relay. Available in 3-wire (Line-Line) or 4-wire (Line-Neutral) voltage configurations, it provides industry-standard analog outputs proportional to the connected voltage.



Power Monitoring Applications

True RMS Voltage Monitoring

- Detect below normal or "brownout" voltage conditions to prevent motor overheating.
- Monitor sinusoidal or non-sinusoidal (variable frequency) waveforms in relevant applications.
- Identify over-voltage conditions associated with regenerative voltage to diagnose and avoid motor drive issues.
- Detect voltage conditions that could stress or damage soft start components.
- Identify phase loss conditions by detecting voltage reduction.



3-Phase Voltage Transducer Features

Monitor 3-Phase Voltage Inputs

- Measures True RMS voltage individually for all three phases.
- Provides an additional output with the average RMS voltage across all three phases.
- Ideal for challenging electrical environments and non-sinusoidal power applications like VFDs.

Industry Standard Output Options

- Offers industry-standard output options (4-20 mA, 0-5 or 0-10 VDC).
- · Compatible with existing PLC controllers, data loggers and SCADA equipment.

Phase Loss Detection

• SPST Form A relay activates when voltage drops below threshold.

Externally Powered

• Externally powered (120 VAC) with low consumption.

UL/cUL Listed, CE Certified

Accepted worldwide.

Mount Options

- Snap case onto a DIN rail, or mount directly to panel using screws.
- Need a DIN Rail? The optional DIN Rail Kit (DINKIT) includes a 175 mm wide DIN rail and two end stops.





(№) (€

Voltage Transducer Dimensions





Voltage Transducer Connections



	C = 03
Power Supply	120 VAC (+/-10%) @ 50/60 Hz
Power Consumption	<6 VA 0-5, 0-10 V output <9 VA 4-20 mA output
Input Range Line-Line Line-Neutral	0-150, 0-300, 0-600 VAC @ 50/60 Hz 0-150, 0-300 VAC @ 50/60 Hz
Input Impedance	400 ΚΩ
Output Signal	 4–20 mA (capped at 20 mA) 0–5 VDC (capped at 5 VDC) 0–10 VDC (capped at 10 VDC)
Response Time	200 ms (to 90% step change)
Accuracy	<1% FS
Output Loading	• 4–20 mA output: <500 Ω • 0–5/0-10 VDC output: >10 KΩ
Phase Loss Detection Relay	SPST Form A Relay Contact 1 A @ 30 VDC; 0.5 A @ 125 VAC
Isolation Voltage	1250 VAC
Case	UL94 V-0 Flammability Rated noncorrosive thermoplastic
Environmental	-4 to +140°F (-20 to +60°C) 0–95% RH, non-condensing
Listings	UL/cUL (<u>E129625</u>), CE

Voltage Transducer Specifications

Voltage Transducer Ordering Information

Sample Model Number: VT3-LL2-420-120-OL Three-phase voltage transducer, 0-300 VAC Line-Line input with proportional 4-20 mA output, powered by 120 VAC in a DIN rail compatible case.

	(1)				(2)				(3)				(4)		
VT3 –	L	L	2	-	4	2	0	-	1	2	0	-	0	L	

(1)	Danaa
	Range
· · · /	

LL1	0-150 VAC, Line-Line, Phase Loss @ 90 VAC		
LL2	0-300 VAC, Line-Line, Phase Loss @ 180 VAC		
LL3	0-600 VAC, Line-Line, Phase Loss @ 360 VAC		
LN1	0-150 VAC, Line-Neutral, Phase Loss @ 90 VAC		
LN2	0-300 VAC, Line-Neutral, Phase Loss @ 180 VAC		
(2) Output			
420	4-20 mA		
005	0-5 VDC		
010	0-10 VDC		
(3) Power S	Supply		
120	120 VAC		
(4) Case Style			
OL	DIN Rail or Panel Mount		



